

# FDP 4.600 V2

## Full Range Class D 4-Channel amplifier

- **Small size**

Easy integration in a vehicle

- **Compact Aluminum chassis**

High thermal dissipation

- **High-pass, low-pass, and band-pass crossover**



- **4G Power & Ground Terminals**

- **Remote sub control with LED clipping indicator**



- **High and low-level inputs**

Suits any installation

- **“Auto Power On” with high-level input**

Easier Integration with factory head unit

- **Selectable Balanced or Unbalanced inputs**

- **Designed & Engineered in California**

Unique amplifier design

- **High-pass, low-pass, and band-pass crossover**

To accommodate complex 3-way systems

### ADVANTAGES

- Very small size for power output
- Can be used in 2, 3, or 4 channel modes
- High-level input, compatible with OEM Stereo
- Easily accessible settings
- Remote sub control
- Invisible mounting bracket
- Highest level of crossover flexibility

### TECHNICAL CHARACTERISTICS

**Power into 4 Ohms:** 4x150 wRMS @ 1% THD

**Power into 2 Ohms:** 4x200 wRMS @ 1% THD

**Bridged mode into 4 Ohms:** 2x400 wRMS @ 1% THD

**DO NOT Bridge into 2 Ohms**

**Frequency response:** 5Hz-25kHz

**Signal/noise ratio:** 90dB

**Adjustable gain:** 200mV + 10V

**Dimensions (HxLxD):** 1.97in x 10in x 7.71in (50x254x196mm)

**Protections:** Short-circuit, thermal overload, polarity reversal, DC

