

FDP 4.600

Full Range Class D 4-Channel amplifier

- Small size
Easy integration in a vehicle
- High-pass, low-pass, and band-pass crossover
- Compact Aluminum chassis
High thermal dissipation
- High and low-level inputs
Suits any installation
- "Auto Power On" with high-level input
Easier Integration with factory head unit
- Selectable Balanced or Unbalanced inputs
- Designed & Engineered in California
Not a "me too" amplifier design
- 4G Power & Ground Terminals
- Remote sub control
with LED clipping indicator

ADVANTAGES

- Very small size for power output
- Can be used in 2, 3, or 4 channel modes
- High-level input, compatible with OEM Stereo
- Easily accessible settings
- Remote sub control
- Invisible mounting bracket
- Highest level of crossover flexibility

TECHNICAL CHARACTERISTICS

Power into 4 Ohms: 4x150W rms
Power into 2 Ohms: 4x200W rms
Bridged mode into 4 Ohms: 2x400W rms
Frequency response: 5Hz–25kHz
Signal/noise ratio: >95dB (A)

Adjustable gain 200mV to 19V
Dimensions (HxLxD): 2 x 10 x 7^{3/4} in
(50x254x196mm)
Protections: Short-circuit, continuous current,
thermal overload, polarity reversal, DC

